



ADVICE TO ALL CONTRACTORS

TREAT ALL OVERHEAD LINES, DUCTS AND ELECTRICITY CABLES AS "LIVE" UNTIL POSITIVELY PROVEN OTHERWISE

Please ensure safe working practices are followed when working near overhead lines, power poles, underground electricity cables and ducts. Refer to the following table for minimum safe working distances which must be observed, when working with mechanical plant and hand held power tools:

Safe Working Distances (Minimum)

Overhead Lines	4.0m	For <u>exemptions</u> contact Alpine Energy Control Room, Ph 0800 66 11 77 extension 324 to arrange a close approach permit. Excavated or other material shall not be deposited under or near an overhead line so as to reduce the conductor clearance to ground.
Power Poles	2.2m (from base of pole)	Unless a consent has been obtained from Alpine Energy Ltd No excavations shall be at a depth greater than 750mm between 2.0m and 5.0m from the pole.
Electricity Cables and Ducts	0.5m	Refer notes below for OSH safe working practices when working near *Electricity cables and ducts.

* Electricity Cables and Ducts

Safe working practises are defined in the OSH publication: Guide for Safety with Underground Services (2002);

- **Obtain Cable Plans**
Forward a location plan showing extent of excavation works to Alpine Energy Ltd.
Allow a minimum of 2 working days notification
Alpine Energy Ltd will supply all available plans at no cost.
NOTE: *There may be other power cables in the vicinity of the proposed works which are not the responsibility of Alpine Energy Ltd (e.g. lighting and private power cables).*
- **Locate Cable Position From Plan and Verify With a Pipe/Cable Locator**
OSH recommendations are that contractors should where possible verify the cable position from the plan with a Pipe/Cable Locator.
- **Hand Expose Cables**
It is the contractor's responsibility to expose by hand all cables and ducts before mechanical excavation and please ensure that the **total number** of cables either indicated on plans, located on site, or as instructed are accounted for as there may be multiple cables in close proximity in one trench or in separate trenches.

Issued Plans

All plans issued for a job will need to be destroyed after the job is completed as these plans are continually being updated by Alpine Energy and may be out of date. It is the intention of the advice in this document to prevent harm to people, to minimise damage to property and inconvenience to customers.

IF IN DOUBT CONTACT ALPINE ENERGY - Ph 0800 66 11 77

Barrie Cameron
Asset Manager